

VERSA QUICKTALK PRO 2

The Best
SRRS Radio
for business!

- No yearly NTC fees
- 16-Channel Talkgroups
- Robust Design



No.1*
SRRS
radio in the
Philippines

*Based on NTC
registration data

VERSA QUICKTALK PRO 2



MAIN FUNCTION

- | | |
|-----------------------------|------------------------------|
| CTTCS/DCS | Low Battery Alert |
| Remote Kill/Stun/Revive | Time-out Timer |
| PC Programmable | Channel Bandwidth |
| Busy Channel Lockout | Busy Channel Lock Out (BCLO) |
| Monitor Open Squelch | VOX |
| Channel Number Annunciation | Compander |
| Emergency Alarm Function | Scrambler |
| Multi-Scan | |
| Scan Add/Del | |

GENERAL SPECIFICATIONS

Frequency Range	325.000-325.4875 MHz	Operating Temperature	-20°C ~ +60°C
Frequency Stability	±2.5ppm	Antenna Impedance	50Ω
Channel Capacity	16	Battery Capacity	2600mAh (Li-ion)
Channel Spacing	12.5/25KHz	Battery Life (5-5-90 Duty Cycle)	15 Hours
Operating Voltage	7.4V	Dimensions (H*W*D) w/o Antenna	117 x 54 x 34mm
Weight	274g		

RECEIVING

Rated Audio Power Output	500mW	Intermodulation	60dB
Rated Audio Distortion	≤ 5%	Adjacent Channel Selectivity	60dB
Sensitivity	≤0.30μV; 0.22μV	Spurious Response Rejection	65dB
S/N	40/45dB		

TRANSMITTING

RF Power Output	2.5W	Audio Distortion	≤ 5%
Modulation Type (Analog)	F3E	Modulation Limitation	±2.5KHz @12.5KHz; ±5KHz@25KHz
Modulation Limit	60dBc	Audio Response	+1 to -3dB
Spurious & Harmonics	-40/45dB		

STANDARD ACCESSORIES



OPTIONAL ACCESSORIES



VERSA INNOVATIONS CORP.
No. 35 Liberty Ave. cor. 9th Ave.,
Brgy. Socorro, Cubao, Quezon City 1109

VERSA retains the right to change the product design and specifications without notices.
If any printing mistake occurs, VERSA will not bear any relevant responsibility.

www.versa.ph

Contact Us: